




SM 15K - Series 15kW DC POWER SUPPLIES

Bi-Directional - Constant Power

Models	Voltage range	Current range
SM 500-CP-90	0 ... 500 V	-90 ... 90 A



Features

- Bi-Directional power supply, standard 15kW Source & Sink
- Flexible output with constant power characteristic
- Power Regeneration Technology: sink power is not dissipated but fed back into the grid
- Designed for long life at full power
- Excellent dynamic response to load changes, digital controlled with the possibility to adapt to the type of load
- Very low heat dissipation, efficiency > 95%
- Protected against all overload and short circuit conditions

Functionalities

- Operation on a wide range of three phase AC input voltages
- Standard Ethernet & Web interface
- EMC surpasses CE requirements: low emission & high immunity
- Low audible noise: temperature controlled cooling fans
- Durable digital encoders for voltage & current adjustment and menu operation
- Large user display, menu driven operations

		SM500-CP-90
DC Power terminals		
voltage		0 ... 500 V
current		-90 ... 90 A
AC Input		
3 phase, 48 - 62 Hz		342 ... 528 V
rated voltage range		380 ... 480 V
rated frequency		50 / 60 Hz
rated current		Max. 27 A
current (400 V / 3 ph, 15 kW)		23 A
power factor, 15 kW, 7,5 kW		0.996, 0.988
internal fuses		30 AT
standby AC input power ($V_o=I_o=0$)		96 W
standby AC input power ($V_o=V_{max}$)		180 W
Efficiency		
Sink & Source mode:		
400 V AC, 3 ph input,		
15 kW, 167 V, 90 A		95 %
15 kW, 500 V, 30 A		96 %
Regulation		
Load 0 - 100%	CV	2 mV
Line 342 - 528 V AC	CV	< 1 mV
(external voltage sense)		
Load 0 - 100%	CC	8 mA
Line 342 - 528 V AC	CC	1 mA
(internal voltage sense, after warm-up)		
Ripple + noise		
Source mode 167 V / 90 A:		
rms (BW=300 kHz)	CV	10 mV
p-p (BW=20 MHz)	CV	55 mV
rms (BW=300 kHz)	CC	45 mA
p-p (BW=20 MHz)	CC	200 mA
Source mode 500 V / 30 A:		
rms (BW=300 kHz)	CV	20 mV
p-p (BW=20 MHz)	CV	100 mV
rms (BW=300 kHz)	CC	45 mA
p-p (BW=20 MHz)	CC	200 mA
Sink mode 167 V / 90 A:		
rms (BW=300 kHz)	CV	7 mV
p-p (BW=20 MHz)	CV	35 mV
rms (BW=300 kHz)	CC	45 mA
p-p (BW=20 MHz)	CC	200 mA
Sink mode 500 V / 30 A:		
rms (BW=300 kHz)	CV	10 mV
p-p (BW=20 MHz)	CV	50 mV
rms (BW=300 kHz)	CC	90 mA
p-p (BW=20 MHz)	CC	320 mA
<i>CC-ripple at full load</i>		
Minimum Sink Voltage		
Sink current:		
-90 A		5.5 V
-30 A		3.0 V
-10 A		1.0 V
Temp. coeff., per °C⁻¹		
	CV	$20 \cdot 10^{-6}$
	CC	$50 \cdot 10^{-6}$
Stability¹		
after 1 hr warm-up		
during 8 hrs	CV	$50 \cdot 10^{-6}$
	CC	$80 \cdot 10^{-6}$
$t_{amb} = 25 \pm 1 \text{ °C}$, $V_{in} = 400 \text{ V AC}$		
internal voltage sensing for CC-stab.		

- Notes:
1. Measured at full load
 2. Signal latency depends on the interface used and data traffic.
 3. See 'Safety Instructions' in the manual.
 4. The optional interfaces are under development.

Programming speed ² <i>Standard Version</i> (resistive load)	SM500-CP-90	
Rise time (10 - 90%) output voltage step time, (load = 15 kW) time, (load = 1500 W)	0 → 167 V 1.5 ms 1 ms	
output voltage step time, (load = 15 kW) time, (load = 1500 W)	0 → 500 V 4.5 ms 3.5 ms	
Fall time (90 - 10%) output voltage step time, (load = 15 kW) time, (load = 1500 W)	167 → 0 V 0.8 ms 0.9 ms	
output voltage step time, (load = 15 kW) time, (load = 1500 W)	500 → 0 V 2.5 ms 3.5 ms	
DC Output Capacitance X-capacitors (typical) Y-capacitors (typical)	560 µF 145 nF	
Programming speed ² <i>High Speed Version</i> (resistive load)	SM500-CP-90 <i>Not yet available</i>	
Rise time (10 - 90%) output voltage step time, (load = 15 kW) time, (load = 1500 W)	0 → ... / ... V ... / ... ms ... / ...ms	
output voltage step time, (load = 15 kW) time, (load = 1500 W)	
Ripple @ full load typical (rms / pp)	... mV / ... mV	
Fall time (90 - 10%) output voltage step time, (load = 15 kW) time, (load = 1500 W)	... / ... → 0 V ... / ... ms ... / ... ms	
output voltage step time, (load = 15 kW) time, (load = 1500 W)	
DC Output Capacitance X-capacitors (typical) Y-capacitors (typical)	... µF ... nF	

	SM500-CP-90	
Recovery time output voltage	167 V, load step 45 → 90 A	500 V, load step 15 → 30 A
recovery within	500 mV	500 mV
di/dt of load step	1.5 A/µs	0.5 A/µs
output voltage	167 V	500 V
time, @ 50 - 100% load step	100 µs	150 µs
max. deviation	2.8 V	1 V
Pulsating load max. tolerable AC component of load current	... Arms	
f > 1 kHz	... Apeak	
f < 1 kHz		


Insulation AC pwr terminals / DC pwr terminals creepage / clearance	3750 Vrms (1 min.) 8 mm
AC power terminals / case DC power terminals / case	2500 Vrms ³ 1000 V DC ³
Safety	EN 60950 / EN 61010

Notes: 1. Measured at full load
2. Signal latency depends on the interface used and data traffic.
3. See 'Safety Instructions' in the manual.
4. The optional interfaces are under development.

Typical Applications


- Solar inverter testing, PV-Simulation
- Car testing systems
- ATE in industrial production lines
- Plasma chambers
- Automotive battery simulations
- Controlled battery (dis)charging
- Lasers
- Sustainable energy
- Driving PWM-Controlled DC motors
- Accurate current sources
- Aerospace and military equipment

Standard Features



Bi-Directional Two-Quadrant Output

Full power Bi-Directional two quadrant operation maintains the DC output voltage constant whether the output power is positive or negative. Ideal for PWM-speed controlled DC-Motors and ATE systems.



Digital CV-, CC- and CP-Settings

Reliable, longlife digital encoders are implemented at the front panel. Includes total front panel lock (also for CV- / CC-knobs) and a coarse or fine pitch adjustment depending on the turning speed.




Sequencer

Arbitrary Waveform generator or standalone automation.




High Voltage Isolation

A high DC output isolation allows series operation up to 1000 V.



Ethernet Interface

Ethernet interface for programming and monitoring.



USB-Input

Not yet available: Front and rear panel USB-Input for exchange of settings and waveforms (Host / Type-A), or for controlling the unit (Device / Type-B).

Options



Software Control and Interfaces

Field installable interfaces:

- Digital I/O
- Isolated Contacts
- Serial controller with multiple protocols RS 232, RS 485, RS 422 and USB (Device)

Order Codes :

- INT MOD DIG
- INT MOD CON
- INT MOD SER

Under development are:

- Simulation Interface
- Isolated Analog Programming
- Master / Slave controller



High Speed Programming

High speed programming is under development.

